



RCD to CTC2 Pin Out continued

RCD Card Front			RCD Card Back		
RCD Card Signal	DIMM Pin	CTC2 Signal	RCD Card Signal	DIMM Pin	CTC2 Signal
CS0_B_N	76	CS0_B_n	CA3_A	213	CA3_A
CA0_B	78	CA0_B	CA5_A	215	CA5_A
CA2_B	80	CA2_B	DCK_t	217	CK_t
CA4_B	82	CA4_B	DCK_c	218	CK_c
CA6_B	84	CA6_B	CS1_B_N	221	CS1_B_n
RSP_A_n, RFU	86	RSP_A_n, RFU	CA1_B	223	CA1_B
RSP_B_n/RFU	87	RSP_B_n, RFU	CA3_B	225	CA3_B
BCOM0_B	89	CB0_B	CA5_B	227	CA5_B
BCOM1_B	91	CB1_B	PAR_B	229	PAR_B
BCK_B_c	93	DQS4_B_t	RFU	231	RFU
BCK_B_t	94	DQS4_B_c	RFU	232	RFU
DLBS_B	96	CB4_B	BCS_B_N	234	CB2_B
DLBD_B	98	CB5_B	QRST_B_N	236	CB7_B
DERR_B_N	100	DQ0_B	QLBS	238	DQS4_B_c
			BCOM2_B	241	CB6_B
QACK_B_t	104	DQS0_B_t	BRST_B_N	243	CB3_B
QACK_B_c	105	DQS0_B_c			
QACS0_B_N	107	DQ4_B	QCCK_B_t	249	DQS5_B_c
QACA8_B	109	DQ5_B	QCCK_B_c	250	DQS5_B_t
QACA7_B	111	DQ8_B	QACS1_B_N	252	DQ6_B
QACA8_B	113	DQ9_B	QACA5_B	254	DQ7_B
QACA9_B	116	DQS1_B_c	QACA0_B	256	DQ10_B
QACA3_B	118	DQ12_B	QACA2_B	258	DQ11_B
QACA10_B	120	DQ13_B	QACA4_B	260	DQS6_B_c
QACA13_B	122	DQ16_B	QACA6_B	263	DQ14_B
QBCS1_B_N	124	DQ17_B	QACA12_B	265	DQ15_B
QDCK_B_c	126	DQS2_B_t	QBCA0_B	267	DQ18_B
QDCK_B_t	127	DQS2_B_c	QACA11_B	269	DQ19_B
QBCA4_B	129	DQ20_B	QBCS0_B_N	272	DQS7_B_t
QBCA6_B	131	DQ21_B	QBCA5_B	274	DQ22_B
QBCA8_B	133	DQ24_B	QBCA2_B	276	DQ23_B
QBCA9_B	135	DQ25_B	QBCA1_B	278	DQ26_B
QBCA13_B	138	DQS3_B_c	QBCA7_B	280	DQ27_B
QBCA3_B	140	DQ28_B	QBCK_B_t	282	DQS8_B_c
QBCA12_B	142	DQ29_B	QBCK_B_c	283	DQS8_B_t
RFU	144	RFU	QBCA11_B	285	DQ30_B
			QBCA10_B	287	DQ31_B